

Solid State Amplifiers

> compact PJC-LCD series

PJ1002C-LCD



PJ1002C-LCD front view

Features

- > **PRIMARY APPLICATION:** uncompromised amplification power at a very attractive price. Ideal for small to medium power stations.
- > **AMPLIFIER FEATURES:** high-gain amplifier with very low input drive power requirement and adjustable power output from 10 to 100 %.
- > **HARDWARE FEATURES:** extremely compact and rugged thanks to the stainless steel chassis, in only 2HE.
- > **USER-FRIENDLY FEATURES:** four pushbuttons for user/device interaction and software that offers a simple, intuitive interface.
- > **OPERATING EFFICIENCY:** incorporate a PFC (Power Factor Corrector) power supply, that provides the utmost efficiency for enhanced energy saving and environmental protection, which added to LD-MOSFET technology ensure high efficiency, better than 70% across the bandwidth.

- > **EASE OF MAINTENANCE:** advanced module engineering ensures extreme ease of access and simple maintenance. Includes an high performance air filter. The power supply is plug-in type, easily removable.
- > **RELIABILITY/CONTINUITY:** APC (Automatic Power Control) and Foldback protection ensure reliable operation under any operating conditions.
- > **INTERFACE CONTROL:** total control thanks to microprocessor easily programmed from menu with all key parameters displayed on LCD.
- > **REMOTE CONTROL:** electromechanically controllable and integrable into all digital RVR telemetry systems.
- > **REGULATORY COMPLIANCE:** state-of-the-art technology in full compliance with EC, FCC and CCIR standards.

Caratteristiche

- > **PRIMARY APPLICATION:** potenza di amplificazione senza compromessi ad un prezzo estremamente contenuto. Ideale come complemento per stazioni di piccola e media potenza.
- > **AMPLIFIER FEATURES:** amplificatore ad alto guadagno con potenza di pilotaggio in ingresso estremamente basso e potenza di uscita regolabile dal 10 al 100%.
- > **HARDWARE FEATURES:** estremamente compatto e indeformabile perchè realizzato in chassis di acciaio inox, in sole 2 unità rack.
- > **USER-FRIENDLY FEATURES:** quattro tasti a pressione per l'integrazione fra l'utente e l'apparato unita ad un software intuitivo e semplificato.
- > **OPERATING EFFICIENCY:** per un risparmio di risorse energetiche e ambientali, utilizzano un alimentatore PFC (Power Factor Corrector) che sommato alla tecnologia LD-MOSFET garantisce

- rendimenti elevati, superiori al 70% su tutta la banda.
- > **EASE OF MAINTENANCE:** estrema accessibilità e semplicità di manutenzione grazie ad una avanzata ingegnerizzazione modulare dell'apparato. Include un filtro d'aria ad alte prestazioni. L'alimentatore è di tipo plug-in, facilmente rimovibile.
- > **RELIABILITY/CONTINUITY:** elevata continuità di esercizio garantita in qualsiasi condizione di lavoro attraverso un controllo automatico APC ed una protezione di Foldback.
- > **INTERFACE CONTROL:** controllo completo basato su microprocessore e da menu con lettura su display LCD di tutti i parametri principali.
- > **REMOTE CONTROL:** elettromeccanicamente controllabile ed integrabile in tutti i sistemi di telemetria digitali RVR.
- > **REGULATORY COMPLIANCE:** tecnologia moderna e pienamente rispondente alle normative EC, FCC ed CCIR.

Solid State Amplifiers

BROADCAST
EQUIPMENT

Oirt, JPN &
China Band
others
on request

Technical specifications

Parameter		PJ1002C-LCD
		Value
GENERALS		
Frequency range		FCC - CCIR - OIRT - JPN - CHN
Rated output power		1000 W
Driver power for rated output		15 W
Max input power before protection		20 W
Environmental working conditions		-10 °C to + 45 °C (R.S.L.) / 95% relative Humidity non condensing
POWER REQUIREMENTS		
AC Power Input	AC Supply Voltage	230 VAC ±15%
	Active Power Consumption	1400 W
	Overall Efficiency	Typical 70 %
	Connector	VDE IEC Standard
MECHANICAL DIMENSIONS		
Physical Dimensions	L x H x W	483 mm x 88 mm x 516 mm
Weight		about 11 kg
Cooling		Forced, with internal fan
Acoustic Noise		< 75 dBA
INPUTS		
RF Input		50 Ohm (N type)
OUTPUTS		
RF Output		50 Ohm (7/8" EIA flange type)
RF Monitor		50 Ohm (BNC) approx. -60 dBc
FUSES		
On Mains		2 External fuse F 10 A - 6x30 mm

All pictures are RVR's property and they are only indicative and not binding. The pictures can be modified without notice.
These are general specifications. They show typical values and are subject to change without notice.

CE ! 99/5/CE Revision: 07/15

solid state
amplifiers



Via del Fonditore, 2/2c • Zona Industriale Roveri • 40138 Bologna • Italy
Phone: +39 051 6010506 • Fax: +39 051 6011104 • info@RVR.it • www.RVR.it

