

CFM2-3

FM BANDPASS FILTER

FEATURES

- FM 3 kW bandpass filter
- 2 pole / 200 mm
- adjustable selectivity



ELECTRICAL DATA

TYPE	CFM2-3/CC	CFM2-3/DD
FREQUENCY RANGE	87.5 ÷ 108 MHz	
IMPEDANCE	50 ohm	
RETURN LOSS	≥32 dB at carrier f0	
SELECTIVITY stop band atten. 20 dB	± 1.6 ÷ ± 2.0 MHz	
MAX INPUT POWER	3.0 kW (selectivity ± 2.0 MHz) 2.5 kW (selectivity ± 1.6 MHz)	
INSERTION LOSS	See table below	
CONNECTORS	7/8" Unfl.F	1-5/8" Unfl.F
OPERATING TEMPERATURE RANGE	-10 ÷ +45 °C	
OVER TEMPERATURE*	typical 30K at max input power	
MATERIALS	Brass, aluminium, invar, teflon	
EXTERNAL FINISHING	Painted Ral 9005	
WEIGHT	17.5 kg	

* referred to Ambient Temperature. Recommended: [AmbientTemp. + OverTemp.] ≤60°C

INSERTION LOSS at carrier f0 (dB)

FREQUENCY (MHz)		87.5	98	108
SELECTIVITY (MHz)	± 2.0	0.24	0.29	0.30
	± 1.6	0.29	0.34	0.35

